



## »» Features

- Pure sine wave solar inverter
- Built-in 40A MPPT solar charger
- PV input voltage range 20~150VDC (for 1000W), 30~150VDC (for 1500W)
- Built-in anti-dust kit for harsh environment
- Smart battery charge design to optimize battery life
- meet rich customized demands
- Solar energy is provided directly to the load first

## »» Product Data Sheet

MODEL	VICTOR NMS-1000-12	VICTOR NMS-1500-24
Rated Power	1000W/1000VA	1500W/1500VA
<b>AC INPUT</b>		
Voltage	230VAC	
Selectable Voltage Range	170~280VAC(For Personal Computers) 90~280VAC(For Home Appliances)	
Frequency Range	50 Hz/60Hz(Auto sensing)	
<b>AC OUTPUT</b>		
AC Voltage Regulation	230VAC±5%	
Surge Power	2000VA	3000VA
Efficiency(Peak)PV to INV	98%	
Efficiency(Peak)Battery to INV	94%	
Transfer Time	10 ms	
<b>BATTERY</b>		
Battery Voltage	12VDC	24VDC
Floating Charge Voltage	13.5VDC	27VDC
Overcharge Protection	16VDC	32VDC
<b>SOLAR CHARGER &amp; AC CHARGER</b>		
Solar Charger Type	MPPT	
Maximum PV Array Power	600W	1200W
MPPT Range @ Operating Voltage	20~150VDC	30~150VDC
Maximum PV Array Open Circuit Voltage Solar	150VDC	
Maximum Solar Charging Current	40A	
Maximum AC Charging Current	40A	
Maximum Solar+AC Charging Current	80A	
<b>PHYSICAL</b>		
Dimension, D*W*H(mm)	290*240*91	
Cartoon Dimension, D*W*H(mm)	340*295*145	
Net Weight(kgs)	3.5	3.6
Gross Weight(kgs)	4.0	4.2
<b>ENVIRONMENT</b>		
Humidity	5% to 95% Relative Humidity(Non~condensing)	
Operating Temperature	-10°C~50°C	
<b>STANDARD</b>		
Compliance Safety	CE	



### Suzhou Preta Intelligence and Technology Co.,Ltd

No..55 Shangxiang Road, Huaqiao Corporation Head Quarter Centre,

Kunshan City, Suzhou City, China

Tel: 0512-36684019

Mail: info@pretapower.com

Web: <https://pretapower.com/>

